

FEATURE

- 1. ABS Panel
- 2. RFID control
- 3. Level management: master, manager and user.
- 4. Motorized lock case with integrated installation
- 5. Door thickness 5-22mm

APPLICATION

- 1. Private drawer, wardrobe and cabinet
- 2. locker in gym, pool center, school etc.

Step 1. Set up Master Code

- \rightarrow Use a card touch the induction zone, a beep, master card has been set up Note:
- 1 A lock has only a master card
- 2 Master card is used for setting, and can't unlock the door.

Step 2. Set up Manager Card

- → Use master card touch the induction zone, light flashing,
- ightarrow Use a new card touch the induction zone, a beep, manager card has been set up Note:
- ① A lock has only a manager card
- 2 Manager card can unlock the door when the guest lost his cards

Step 3. Set up User Card

- → Use manager card touch the induction zone, light flashing
- → Use a new card touch the induction zone, a beep, user card has been set up

Step 4 (for option). Set up service card (two cards to open the lock)

- → Use manager card touch the induction zone twice, light flashing
- $\,\rightarrow\,$ Use a new card touch the induction zone, light off, service card has been set up

Note:

After setting the service card, it need the user card and service card to open the lock together.